


Freewheel Clutches

Backstops • Overrunning Clutches • Indexing Freewheels



North American Edition 2015/2016



Table of Contents



Freewheel Technology Introduction							Page
later de et en							
Introduction							- 3
Design and Function of Freewheels							4
Applications of Freewheels							
Applications for Freewheels							
Types to extend service life							3
Determination of Selection Torque		Used as		\4/:+b	Marringung	Marringung	Daga
Complete Freewheels	Backstops	Overrunning Clutch	Indexing Freewheel	With bearing support	Maximum torque lb-ft	Maximum bore inch	Page
for bolting to the face	I			I.			
FRS and FRSG with sprags	0		0	0	55 000	7.000	10
FRX and FRZ with sprag lift-off X or lift-off Z	0		0		30 000	5.438	12
with torque arm							
FRXF with sprag lift-off X, sealed grease lubricated ball bearings	0			0	14500	4.500	14
FRHD with sprags	0			0	2400000	21.000	16
FRHM with sprags				0	56000	7.000	18
FA with sprags and grease lubrication			•	0	3690	3.150	20
with torque arm and clamping collar or mounting flange			_				
RFB with sprags and grease lubricated ball bearings	0			0	900	6.000	22
with shaft coupling							
FR CA with sprags				0	55 000	7.000	24
Accessories for Complete Freewheels FR Torque Arms TA							27
End Covers							27
Internal Freewheels		Used as		With	Maximum	Maximum	Page
	Backstops	Overrunning Clutch	Indexing Freewheel	bearing support	torque lb-ft	bore inch	
for press fit on the outer ring							
ZZ with sprags, bearing supported	0		•		480	1.575	28
ZZ 2RS with sprags, bearing supported and sealed	0		0		480	1.575	30
ZZ P2RS with sprags, bearing supported and sealed	0		0		480	1.575	30
ZZ P with sprags, bearing supported					480	1.575	31
for keyway connection on the outer ring							
ZZ PP with sprags, bearing supported	0		0		480	1.575	31
RC with sprags					1 240	2.200	32
specifically designed as interchange backstops for Dodge® reducers							
RCD with sprags	0				Dodge® S	Standard	33
Interchange Charts							Page
for Marland, Formsprag, Morse®/EPT and Renold with RINGSPANN Free	ewheels						34
FRHD Series - for Formsprag, Marland, Falk, Stephens Adamson and Mo	orse®						35
Questionnaires							Page
for selecting RINGSPANN Backstops							36
for selecting RINGSPANN Overrunning Clutches							37
for selecting RINGSPANN Indexing Freewheels							38

Issue 09/2015 • Technical details subject to change without notice.

Dodge® is a registered trademark of Baldor Electric Company. • Morse® is a registered trademark of Borg Warner.



RINGSPANN GmbH has been in business for over 70 years and is a world leader in Power Transmission and Workholding Technology. RINGSPANN CORPORATION, as a wholly owned subsidiary of RINGSPANN GmbH, designs, manufactures and assembles sprag and roller clutches mainly for the North American market. With innovative German engineering and American ingenuity, RINGSPANN CORPORATION offers the winning combination of quality products for your needs.

Products contained in this catalog represent RINGSPANN CORPORATION's standard free-wheel clutches. Located in a 20,000 sq. ft. manufacturing facility, RINGSPANN CORPORATION can readily design new or modify existing products to suit your application.

The RINGSPANN CORPORATION service advantage:

- Detailed application support backed by over 70 years of experience.
- Direct sales and service from the manufacturer
- 24 hour emergency service
- North American industry leader for
 - Price
 - Delivery
 - Customer service
 - Quality

The RINGSPANN CORPORATION design advantage:

- · American design and manufacture
- Patented sprag cage designs for increased torque and maximum life
- Maximum torque in a minimum space
- Sprag Lift off "X" and "Z" for infinite, maintenance free life
- Individual springs on every sprag to provide added security against failures



Design and Function of Freewheels



Freewheels are machine elements with particular characteristics:

- In one direction of rotation there is no contact between the inner and outer ring; the freewheel is in freewheeling operation.
- In the opposite direction of rotation there is contact between the inner and outer ring; in this direction it is possible to transmit torque.

For example the outer ring of the freewheel shown in figure 4-1 can freewheel clockwise while the inner ring is stationary. If, however, the outer ring is turned in the opposite direction, there is contact between the inner and outer ring and the inner ring is driven (driving operation).

Freewheels are used as:

- Backstops
- Overrunning Clutches
- Indexing Freewheels

Freewheels can fulfill these functions completely automatically in the most diverse machines. No mechanical or hydraulic operating equipment is required, such as externally actuated clutches or brakes.


Freewheels consist of an inner and an outer ring between which clamping elements are arranged. Clamping elements can be sprags or rollers. We differentiate as follows:

- · Freewheels with bearing support and
- Freewheels without bearing support.


For a freewheel to function, concentric alignment of the inner and outer ring is required. In the case of freewheels without bearing support, concentric alignment must be provided by the customer.

RINGSPANN freewheels are an indispensable design element in the machine building industry. Many designs are only economical if freewheels are used. The freewheel as an automatic driving element is preferred to conventional solutions because it offers the following significant advantages:

- safe
- · efficient
- high degree of automation



With more than 50 years experience in the development, production and sales of freewheels, RINGSPANN offers the most comprehensive range of freewheels. A global network of subsidiaries and sales agencies ensures the best possible personal on-site service. Assembly and production facilities in various countries provide fast, reliable delivery.




RINGSPANN®


Backstop

Freewheels are used as backstops if reverse rotation of the operating equipment needs to be prevented. In many machines and installations, for technical safety or functional reasons, it is necessary to ensure that the operating equipment is in just one specific direction of rotation. Backstops are used where legal stipulations require a mechanical safety device be installed for the operation of conveyor systems.

The normal operating mode of a backstop is freewheeling operation; the locking (torque transmission) is performed at zero speed. The immediate engagement of the clamping elements ensures the required high operating safety.



In general, backstops are used where the inner ring freewheels and the stationary held outer ring prevents reverse rotation (figure 5-1).



The more complicated designed backstops where the outer ring freewheels and the stationary held inner ring prevents reverse rotation are rarely used today (figure 5-2).

Overrunning Clutch

The overrunning clutch engages machines or machine parts and automatically interrupts their contact as soon as the driven part of the overrunning clutch is turned faster than the driving part. In many cases, this can replace a more expensive externally actuated clutch.

With overrunning clutches the engagement takes place in the driving operation (torque transmission), while in freewheeling operation the torque transmission between the inner and outer ring is interrupted. In driving operation the speeds of the inner and outer ring are equal, while in freewheeling operation they are different.




Figure 5-3 shows an overrunning clutch where in driving operation the power flow is transferred from the inner ring to the outer ring and in freewheeling operation the outer ring overruns the inner ring at a higher speed.




Figure 5-4 shows an overrunning clutch where in driving operation the power flow is transferred from the outer ring to the inner ring and in freewheeling operation the inner ring overruns the outer ring at a higher speed.

Indexing Freewheel

The indexing freewheel transmits a back and forth motion into a stepped rotation (indexed feed). The RINGSPANN indexing freewheel enables an infinitly adjustable setting of the feed, for precise and quiet operation.




Figure 5-5 shows an indexing freewheel where the outer ring makes the back and forth motion and the inner ring carries out the indexed feed.




Figure 5-6 shows an indexing freewheel where the inner ring makes the back and forth motion and the outer ring carries out the indexed feed.

Applications for Freewheels


Gear units **Electric motors** Gear motors

The backstop prevents reverse rotation of the drive of a conveyor installation if the power fails or the motor is turned off.

Inclined conveyors

Elevators


Bucket elevators



The backstop prevents reverse rotation of the conveyor load if the power fails or the motor is turned off.


Areas of application for Overrunning Clutches

Textile machines **Printing machines**



During normal operation of textile or printing machines, the overrunning clutch separates the auxiliary drive which is used as a starter from the main drive.

Fans



If fans are turned off, the overrunning clutch prevents the flywheel mass from rotating the drive.


Areas of application for Indexing Freewheels

Textile machines **Printing machines**

The indexing freewheel generates an indexed feed in textile and printing machines.

Packaging machines


Filling plants



The indexing freewheel is used in packaging machines and filling plants for an indexed feed.




Fans




The backstop prevents the motor from reverse rotation under the back pressure when it is turned off.

Pumps Compressors




The backstop prevents the motor from reverse rotation under the back pressure when it is turned off.

Pumps Generators




In multimotor drives the overrunning clutch disengages the inactive or lower speed drive.

Roller conveyor




The overrunning clutch ensures that the conveyed material can be pushed or pulled faster over the rollers than the speed of the drive.

High voltage switches



In high voltage switches for tensioning a spring, the indexing freewheel is used in the place of a reduction gear.

Seed spreader



The indexing freewheel replaces a reduction gear in seed spreader.



		Standard type	Type with sprag lift-off X	Type with sprag lift-off Z
		For universal use	To extend service life using sprag lift-off for high speed rotating inner ring	To extend service life using sprag lift-off for high speed rotating outer ring
	Backstop	Up to medium speeds during freewheeling operation (inner or outer ring freewheels)	Up to very high speeds during freewheeling operation (inner ring freewheels)	Up to very high speeds during freewheeling operation (outer ring freewheels)
Use as	Overrunning Clutch	Up to medium speeds during freewheeling operation (inner or outer ring overruns)	Up to very high speeds during freewheeling operation (inner ring overruns)	Up to very high speeds during freewheeling operation (outer ring overruns)
Use	Overru	Up to very high speeds in driving operation (outer or inner ring drives)	Low speeds in driving operation (outer ring drives)	Low speeds in driving operation (inner ring drives)
	Indexing Freewheel	Up to a medium total number of actuations		

In addition to the standard type, RINGSPANN has developed other types to extend service life


for freewheels with sprags. The table above lists the recommended application conditions for

these types.


Type with sprag lift-off X

The sprag lift-off X is used for backstops and overrunning clutches, provided that in free-wheeling operation the inner ring is rotating at high speed and with overrunning clutches that the driving operation is at a low speed. In free-wheeling operation, the centrifugal force Fc causes the sprag to lift off from the sprag track of the outer ring. In this operating state, the freewheel operates wear-free with unlimited service life.

Figure 8-1 shows a freewheel with sprag lift-off X in freewheeling operation. The sprags, which are supported in a cage connected to the inner ring, rotate with the inner ring. The centrifugal force F_C that is applied in the center of gravity S of the sprag turns the sprag counterclockwise and rests against the support ring of the cage. This results in the gap "a" between the sprag



and the sprag track of the outer ring; the freewheel works without contact. If the inner ring speed decreases to such an extent that the effect of the centrifugal force on the sprag is less than that of the spring force F_F , the sprag again




rests on the outer track and the freewheel is ready to lock (figure 8-2). If used as an overrunning clutch, the driving speed must not exceed 40% of the lift-off speed.


Type with sprag lift-off Z

The sprag lift-off Z is used for backstops and overrunning clutches, provided that in free-wheeling operation the outer ring is rotating at high speed, and with overrunning clutches that the driving operation is at a low speed. In free-wheeling operation, the centrifugal force Fc causes the sprag to lift off from the sprag track of the inner ring. In this operating state, the freewheel operates wear-free with unlimited service life.

Figure 8-3 shows a freewheel with sprag lift-off Z in freewheeling operation. The sprags rotate with the outer ring. The centrifugal force F_C that is applied in the centre of gravity S of the sprag turns the sprag counterclockwise and rests against the outer ring. This results in the gap "a" between the sprag and the sprag track of the



inner ring; the freewheel works without contact. If the outer ring speed decreases to such an extent that the effect of the centrifugal force on the sprag is less than that of the spring force F_F



, the sprag again rests on the inner track and the freewheel is ready to lock (figure 8-4). If used as an overrunning clutch, the driving speed must not exceed 40% of the lift-off speed.

Determination of Selection Torque



Selection torque for Backstops

Bringing a loaded inclined conveyor, an elevator or a pump to a standstill is a highly dynamic process that incurs high peak torques. These peak torques are critical in the selection of the backstop. The determination of peak torques in the case of locking is more accurate by using a rotational vibration analysis of the entire system. This requires a knowledge of rotational masses, the rotational rigidity and the excitation moments that occur in the system. In many cases, a vibrational calculation is too time consuming or you may not have all the necessary data in the configuration phase available. In this case, the selection torque M_{A} of the backstop should be determined as follows:

 $M_A = 1.75 \cdot M_L [lb-ft]$

Often you only have the figures for the motor nominal output P_0 [hp] available. Then:

 $M_A = F \cdot 5250 \cdot P_0/n_{SP}$ [lb-ft]

In these equations:

 M_A = Selection torque of the backstop [lb-ft]

M_L = Static backdriving torque of the load referring to the backstop shaft [lb-ft]

 P_0 = Nominal power of motor [hp]

n_{SP} = Speed of backstop shaft [rpm]

F = Selection factor (refer to table)

After calculating M_A the backstop size must be selected in accordance with the catalog tables in such a way that in all cases this applies:

 $M_N \ge M_A$

M_N = Nominal torque of the backstop in accordance with the table values [lb-ft]

It must be noted that, with a direct motor start in the locking direction of a backstop, very high peak torques can occur which in turn can destroy the backstop.

Approximate values for F:

Type of installation	F
Conveyor belts, angle up to 6°	0.88
Conveyor belts, angle up to 8°	1.07
Conveyor belts, angle up to 10°	1.21
Conveyor belts, angle up to 12°	1.29
Conveyor belts, angle up to 15°	1.39
Screw pumps	1.51
Ball mills, drying drums	1.26
Bucket conveyors, elevators	1.48
Hammer mills	1.51
Fans, Ventilators	0.49

Selection torque for Overrunning Clutches

In many cases where overrunning clutches are being used, dynamic processes occur that cause high peak torques. In the case of overrunning clutches, the torques that occur during start up must be observed. The peak torques when starting up can, in the case of asynchronous motors – especially when accelerating large masses and when using elastic couplings – significantly exceed the torque calculated from the motor pull-over torque. The conditions for internal combustion engines are similar. Even in normal operation, their degree of irregularity, peak torques can occur that are considerably greater than the nominal torque.

The prior determination of the maximum occurring torque is carried out more accurately by using a rotational vibration analysis of the entire system. This, however, requires a knowledge of the rotating masses, the rotational rigidity and all of the excitation moments that occur on the system. In many cases, a vibrational calculation is too time consuming or you may not have all the necessary data in the configuration phase available. In this case, the selection torque M_{A} of the overrunning clutch should be determined as follows:

 $M_A = K \cdot M_L$

In this equation:

 M_A = Selection torque of the freewheel

K = Operating factor (refer to table)

M_L = Load torque for constant rotating freewheel:

 $= 5250 \cdot P_0/n_{FR}$

 P_0 = Nominal power of motor [hp]

n_{FR} = Speed of the freewheel in driving operation [rpm]

After calculating M_A the freewheel size must be selected in accordance with the catalog tables in such a way that in all cases this applies:

 $M_N \ge M_A$

M_N = Nominal torque of the freewheel in accordance with the table values [lb-ft],

Approximate values for operating factor, K":

Type of driver	K
Electric motors with low start up impact (e.g. DC motors, asynchronous motors with slip rings or soft start couplings), steam turbines, gas turbines	0.8 to 2.5
Electric motors with considerable start up impact (e.g. synchronous or asynchronous motors with direct start)	1.25 to 2.5
Piston engines with more than two cylinders, water turbines, hydraulic motors	1.25 to 3.15
Piston engines with one or two cylinders	1.6 to 3.15

The operating factor K depends on the properties of the driver and the machine. The general rules of mechanical engineering apply here. We know from practice that applications are known where the operating factor K can also assume values of up to 20, e.g. with a direct start-up of asynchronous electric motors in connection with elastic couplings.

Selection torque for Indexing Freewheels

The selection torque for indexing freewheels is, among other things, dependent upon how the back and forth motion is generated (crank

operation, hydraulic cylinders, pneumatic cylinders etc.). It cannot be specified in a simple equation. When stating the maximum torque


to be transmitted, we are happy to advise you regarding the selection torque.

Complete Freewheels FRS and FRSG

RINGSPANN®

for bolting to the face with sprags





Application as

- Backstop
- Overrunning Clutch
- Indexing Freewheel

Features

Complete Freewheels FRS and FRSG are sealed sprag freewheels with ball bearings and ready for installation.

The freewheels FRS are supplied oil-filled.

The freewheels FRSG are supplied grease filled.

Maximum torques up to 55 000 lb-ft.

Bores up to 7 inch. Standard bores in inch dimension are available from stock. Metric bores on request.

Application example

Complete Freewheels FRS 600 in both drive units of a transport system with a conveyor belt that moves both forward and backward (reversible operation). In order to ensure that the conveyor belt is moved under tension, forward movement is driven by drive unit I, reverse movement by drive unit II. The freewheels automatically disengage the respective non working drive, eliminating the need for expensive external clutches or brakes.

For forward movement, drive unit II is started in freewheeling direction of freewheel II; freewheel II is in freewheeling operation and disengages drive unit II from the conveyor belt. Afterwords drive unit I is started in the locking direction of the freewheel I; freewheel I is in driving operation and the conveyor belt is moved forward by drive unit I. The speed of drive unit I is lower than that of drive unit II. Thus freewheel II remains in freewheeling operation and drive unit II is not improperly engaged.

For reverse movement, the drive units are started in reverse order and direction of rotation at the corresponding speeds.


The mentioned application for a reversing conveyor requires speed control for both of the drives.

Conveyors operating in the same direction can use clutches in conjunction with the two drives.

Complete Freewheels FRS and FRSG



for bolting to the face with sprags



11-1

ng Freewheel Inning Clutch Backstop	Standard type For universal use	Standard type - grease lubricated For universal use
Indexir		

			Max. s	peed				Max.s	speed
Freewheel Size	Maximum torque M _M Ib-ft	Nominal torque M _N lb-ft	inner ring freewheels/ overruns rpm	outer ring freewheels/ overruns rpm	Freewheel Size	Maximum torque M _M Ib-ft	Nominal torque M _N lb-ft	inner ring freewheels/ overruns rpm	outer ring freewheels/ overruns rpm
FRS 300	420	210	2500	2600	FRSG 300	420	210	3600	3600
FRS 400	670	335	1900	2100	FRSG 400	670	335	3600	3600
FRS 500	1 600	800	1400	1 900	FRSG 500	1 600	800	3600	3600
FRS 550	3 050	1525	1175	1600	FRSG 550	3 0 5 0	1 5 2 5	3600	3600
FRS 600	3 900	1950	1100	1 500	FRSG 600	3 900	1950	3600	3600
FRS 650	5 400	2700	900	1250	FRSG 650	5 400	2700	3600	3600
FRS 700	11 050	5 5 2 5	790	1150	FRSG 700	11 050	5 5 2 5	1800	1800
FRS 750	18700	9350	790	1150	FRSG 750	18700	9350	1800	1800
FRS 775	17 000	8500	750	1 0 5 0	FRSG 775	17 000	8500	1800	1800
FRS 800	22 200	11 100	700	950	FRSG 800	22 200	11 100	1800	1800
FRS 900	33 600	16800	700	950	FRSG 900	33 600	16800	1200	1 200
FRS 1000	55 000	27500	630	800	FRSG 1000	55 000	27500	1200	1 200

See page 9 for determination of selection torque.

Freewheel					Bore	ed					D	F	G	L	Н	0	T	Z*	Weight
Size				S	tandard bores inch					max. inch	inch	inch	Thread	inch	inch	inch	inch		lbs
FR 300	0.500	0.650	0.750		incii					0.750	3.000		0.250-28	2.500	0.375	0.750	2.625	4	3.5
FR 400	0.500	0.625	0.750	0.875	1.000	1.125				1.125	3.500		0.312-24	2.750	0.500	0.750	2.875	4	6.0
FR 500	0.875	1.000	1.125	1.250	1.312					1.312	4.250		0.312-24	3.500	0.625	1.000	3.625	4	10.0
FR 550	1.250	1.312	1.500	1.625						1.625	4.750	0.063	0.312-24	3.250	0.540	0.750	4.250	6	12.0
FR 600	1.250	1.375	1.438	1.500	1.625	1.688	1.750	1.938	2.000	2.000	5.375	0.063	0.312-24	3.750	0.625	1.000	4.750	6	19.0
FR 650	1.938	2.000	2.250	2.438	2.500					2.500	6.500	0.063	0.375-24	3.500	0.750	1.000	5.750	8	24.0
FR 700	1.938	2.000	2.250	2.438	2.500	2.750	2.938			2.938	7.125	0.063	0.375-24	5.000	0.750	1.000	6.250	8**	42.0
FR 750	2.438	2.500	2.938	3.000	3.250	3.438				3.438	8.750	0.063	0.500-20	6.000	0.875	1.250	7.000	8**	83.0
FR 775	2.750	2.938	3.000	3.250	3.438	3.500	3.750			3.750	9.750	0.063	0.500-20	6.000	0.875	1.250	8.500	8	96.0
FR 800	3.000	3.250	3.438	3.500	3.750	3.937	4.000	4.250	4.500	4.500	10.000	0.063	0.500-20	6.000	0.875	1.250	8.937	8	102.0
FR 900	4.000	4.438	4.500	4.938	5.000	5.438				5.438	12.000	0.063	0.625-18	6.375	1.000	1.375	9.750	10	156.0
FR 1000	5.750	5.938	6.000	6.750	6.875	7.000				7.000	15.000	0.063	0.625-18	6.625	1.000	1.375	11.750	12	250.0

Mounting

The customer attachment part is centered on the external diameter D and then bolted on to the face.

The recommended tolerance of the shaft is +0/ - 0.001 inch and the tolerance of the pilot diameter D of the attachment part is -0/+0.002inch.

Labyrinth Seals

Labyrinth seals are available to provide additional protection for harsh environments.

^{*} Z = Number of tapped holes G on pitch circle T.

** Six holes are equally spaced 60° apart with two additional holes located 30° from the six equally spaced holes and 180° apart.


Keyway dimensions upon request by customers.

Complete Freewheels FRX and FRZ

RINGSPANN®

for bolting to the face with sprag lift-off X or lift-off Z





Application as

- Backstop
- Overrunning Clutch

Features

Complete Freewheels FRX and FRZ are sealed sprag freewheels with ball bearings and sprag lift-off X or sprag lift-off Z.

Maximum torques up to 30 000 lb-ft.

Bores up to 5.438 inch. Standard bores in inch dimension are available from stock. Metric bores on request.


Application example

Complete Freewheel FRX 600 as an overrunning clutch in the drive unit of a conveyor belt system with additional creep drive. The freewheel with shaft coupling is installed between the main motor and the creep drive. When the creep drive operates, the freewheel is in driving operation and drives the belt at low speed. During normal operation (freewheeling operation), the main motor drives and the inner ring overruns and the creep drive is automatically disengaged. With this high speed, sprag lift-off X is used; the sprags work in freewheeling operation without contact and are wear-free.

Complete Freewheels FRX and FRZ



for bolting to the face with sprag lift-off X or lift-off Z



13-1

nning Clutch Backstop	Type with sprag lift-off X To extend service life using sprag lift-off for high speed rotating inner ring	Type with sprag lift-off Z To extend service life using sprag lift-off for high speed rotating outer ring
Overru		

				Max.	speed					Max.s	peed
	Maximum	Nominal	Sprag lift-off	inner ring	outer ring		Max.	Nominal	Sprag lift-off	outer ring	inner ring
Freewheel	torque	torque	at inner ring	freewheels/	drives	Freewheel	torque	torque	at outer ring	freewheels/	drives
Size	M _M	M _N	speed	overruns		Size	M _M	M _N	speed	overruns	
	lb-ft	lb-ft	rpm	rpm	rpm		lb-ft	lb-ft	rpm	rpm	rpm
FRX 400	250	125	860	4000	340	FRZ 400	560	280	800	2600	320
FRX 500	850	425	750	4000	300	FRZ 500	1 070	535	1400	2050	560
FRX 550	1 500	750	700	4000	280	FRZ 550	2760	1380	1550	1 800	620
FRX 600	2 000	1 000	670	4000	265	FRZ 600	3 5 3 0	1765	1450	1650	580
FRX 650	3 500	1750	610	3100	240	FRZ 650	5 0 0 0	2500	1 300	1400	520
FRX 700	8 100	4050	350	2600	140	FRZ 700	10500	5 2 5 0	1160	1 200	465
FRX 750	14600	7300	320	2400	125	FRZ 750	17500	8750	1160	1 200	465
FRX 775	14800	7400	320	2100	125	FRZ 775	15 000	6500	950	1 050	380
FRX 800	29 000	14500	250	1800	100	FRZ 800	17400	8700	880	975	350
FRX 900	30 000	15 000	250	650	100	FRZ 900	26000	13 000	720	925	288

See page 9 for determination of selection torque.

Freewheel					Bor	e d					D	F	G	L	Н	0	T	Z**	Weight
Size				St	andard bores inch	5				max. inch	inch	inch	Thread	inch	inch	inch	inch		lbs
FR 400	0.500	0.625	0.750	0.875	1.000*	1.125*				1.125	3.500	0.032	0.312-24	2.750	0.500	0.750	2.875	4	6.0
FR 500	0.875	1.000	1.125	1.250	1.312					1.312	4.250	0.063	0.312-24	3.500	0.625	1.000	3.625	4	10.0
FR 550	1.250	1.312	1.500	1.625						1.625	4.750	0.063	0.312-24	3.250	0.540	0.750	4.250	6	12.0
FR 600	1.250	1.375	1.438	1.500	1.625	1.688	1.750	1.938	2.000	2.000	5.375	0.063	0.312-24	3.750	0.625	1.000	4.750	6	19.0
FR 650	1.938	2.000	2.250	2.438	2.500					2.500	6.500	0.063	0.375-24	3.500	0.750	1.000	5.750	8	24.0
FR 700	1.938	2.000	2.250	2.438	2.500	2.750	2.938			2.938	7.125	0.063	0.375-24	5.000	0.750	1.000	6.250	8***	42.0
FR 750	2.438	2.500	2.938	3.000	3.250	3.438				3.438	8.750	0.063	0.500-20	6.000	0.875	1.250	7.000	8***	83.0
FR 775	2.750	2.938	3.000	3.250	3.438	3.500	3.750			3.750	9.750	0.063	0.500-20	6.000	0.875	1.250	8.500	8	96.0
FR 800	3.000	3.250	3.438	3.500	3.750	3.937	4.000	4.250	4.500	4.500	10.000	0.063	0.500-20	6.000	0.875	1.250	8.937	8	102.0
FR 900	4.000	4.438	4.500	4.938	5.000	5.438				5.438	12.000	0.063	0.625-18	6.375	1.000	1.375	9.750	10	156.0

^{*} Not available for FRX. Max bore 0.875 inch.

Mounting

The customer attachment part is centered on the external diameter D and then bolted on to the face.

The recommended tolerance of the shaft is +0 / -0.001 inch and the tolerance of the pilot diameter D of the attachment part is -0 / +0.002 inch.

Labyrinth Seals

Labyrinth seals are available to provide additional protection for harsh environments.

^{**} Z = Number of tapped holes G on pitch circle T.

^{***} Six holes are equally spaced 60° apart with two additional holes located 30° from the six equally spaced holes and 180° apart. Keyway dimensions upon request by customers.

Complete Freewheels FRXF



with torque arm with sprag lift-off X and sealed grease lubricated ball bearings



Application as




Features

Complete Freewheels FRXF are freewheels with sprag lift-off X, labyrinth seals, and sealed grease lubricated ball bearings. All units are supplied complete with torque arms. FRXF backstops are maintenance free and lubricated for life prior to shipping.

Maximum torques up to 29000 lb-ft.

Bores up to 4.5 inch. Standard bores are available from stock.



Application example

Complete Freewheel FRXF as backstop, arranged at the end of a high speed shaft of the gearbox. The back driving torque is restrained by the clutch torque arm and the gearbox torque arm pin.


With this high shaft speed under normal operation (freewheeling operation), sprag lift-off X is used; the sprags work in freewheeling operation without contact and are wear-free.

Complete Freewheels FRXF



15-1

with torque arm with sprag lift-off X and sealed grease lubricated ball bearings



Backstop		Type with sp extend service lift or high speed ro			Dime	nsions								
4,														
	Maximum	Nominal	Sprag	Maximum	Α	F	Н	L	М	N	0	R	Torque We	eiaht

Freewheel Size	torque M _M	torque M _N	lift-off at inner ring speed	speed inner ring overruns		Bore d Standard bores ma								'	"	_	141	14	0	I	arm Size	weight
	lb-ft	lb-ft	rpm*	rpm		inch							inch	inch	inch	inch	inch	inch	inch	inch		lbs
FRXF 550	1 500	750	700	4000	1.250	1.312	1.500	1.625				1.625	6.750	3.750	8.313	3.25	1.00	0.813	4.380	4.00	#10	20
FRXF 700	8 100	4050	350	3600	1.938	2.000	2.250	2.438	2.500	2.750	2.938	2.938	9.375	5.250	11.813	5.00	1.25	1.250	5.625	6.00	#20	60
FRXF 775	14800	7300	320	2100	2.750	2.938	3.000	3.250	3.438	3.500	3.750	3.750	13.000	6.375	15.825	6.00	1.50	1.875	6.875	7.76	#60	150
FRXF 800	29 000	14500	250	1800	4.500							4.500	13.000	6.375	15.825	6.00	1.50	1.875	6.875	7.76	#60	160

See page 9 for determination of selection torque.

Mounting

The back driving torque is restrained by the clutch torque arm and the gearbox torque arm pin. It must have clearance of 1/4 inch to 1/2 inch in both radial and axial directions.

Complete Freewheels FRXF are furnished to size for a slip fit on the shaft.

Non lift off clutch varieties are available when operating below sprag lift off speeds.

Lubrication

The freewheels FRXF 700 and larger are supplied with labyrinth seals, sealed grease lubrication ball bearings and required no additional lubrication.


^{*} Maximum recommended operating speed.


Keyway dimensions upon request by customers.

Complete Freewheel FRHD

RINGSPANN®

with torque arm with sprags







Application as

Backstop

for installations with low speeds. The freewheels are designed for the use in inclined conveyor-belts, elevators or pumps. Taconite seals protect the freewheels from contamination with dust or dirt.

Features

Complete Freewheels FRHD with torque arm are sealed sprag freewheels with ball bearings. They are supplied oil-filled and ready for installation. The freewheels are arranged on through shafts or shaft ends.

Maximum torques up to 2400 000 lb-ft.

Bores up to 21 inch.

Application example

Backstop FRHD 900 on the head pulley shaft of an inclined conveyor belt system. The torque arm is bolted to the freewheel. The back driving torque is restrained by the torque arm on the base plate.


Mounting

The backdriving torque is restrained by the torque arm. The torque arm must not be clamped into position. It must have 0.5 inch play in the axial and in the radial direction.

Complete Freewheel FRHD



with torque arm with sprags



Size FRHD 1000 and FRHD 1100 to FRHD 1900

Dimensions

Bac		For universal use												
	>													
	Maximum	Nominal	Maximum	Bore	Α	(D	Е	н		0	Р	Q	Weight
	torque	torque	speed	d	,,			-		-			4	Weight
Freewheel	M _M	MN	inner ring											
Size			freewheels	max.										
	lb-ft	lb-ft	rpm	inch	inch	inch	inch	inch	inch	inch	inch	inch	inch	lbs
FRHD 700	7500	3750	620	3.44	8.00	6.00	5.25	0.50	36.00	6.00	6.75	16.38	32.00	135
FRHD 775	15 000	7500	540	3.75	9.75	8.00	6.00	1.00	42.88	7.50	9.00	20.38	38.00	310
FRHD 800	24000	12000	460	4.50	10.50	10.00	7.00	1.00	43.25	8.00	9.50	22.13	38.00	360
FRHD 900	37000	18500	400	5.44	12.00	10.00	8.00	1.50	54.00	7.63	9.38	22.75	48.00	480
FRHD 950	46 000	23 000	360	7.00	14.00	12.00	10.00	1.50	69.00	8.00	10.00	25.00	62.00	530
FRHD 1 000	56000	28 000	360	7.00	17.00	8.00	9.00	4.13	80.38	8.75	-	23.13	72.00	550
FRHD 1 050	90 000	45 000	360	7.00	14.00	12.00	10.00	1.50	79.00	10.50	12.50	29.00	72.00	600
FRHD 1 100	90 000	45 000	360	7.00	17.00	8.00	9.00	4.13	80.38	10.00	-	23.13	72.00	795
FRHD 1 200	185 000	92 500	250	9.00	23.00	10.00	12.00	4.94	89.00	11.00	-	28.00	78.00	1 300
FRHD 1 300	220 000	110000	220	10.00	25.00	12.00	14.00	5.25	95.00	12.00	-	30.00	82.88	1674
FRHD 1400	280 000	140 000	200	12.00	30.00	18.00	16.00	6.25	107.00	13.00	-	36.00	94.00	2200
FRHD 1450	380 000	190 000	200	12.00	30.00	18.00	16.00	6.25	107.00	15.00	-	36.00	94.00	2500
FRHD 1 500	580 000	290 000	200	12.00	31.00	18.00	15.13	6.25	107.00	17.62	-	36.00	94.00	2440
FRHD 1600	746 000	373 000	140	14.00	32.50	20.00	17.63	6.25	124.00	19.25	-	30.44	108.00	3400
FRHD 1 700	1 250 000	625 000	120	18.00	42.50	24.50	23.00	7.88	140.00	20.00	-	48.00	120.00	7000
FRHD 1800	1800000	900 000	100	21.00	52.00	30.00	26.50	10.50	170.00	23.00	-	54.00	144.00	12 000
FRHD 1900	2400000	1 200 000	60	21.00	52.00	30.00	27.00	10.50	216.00	27.00	-	54.00	192.00	14000


See page 9 for determination of selection torque. • Keyway dimensions upon request by customers.


Standard type

Complete Freewheel FRHM

with torque arm with sprags







Application as



for installations with low speeds. The freewheels are designed for the use in inclined conveyor-belts, elevators or pumps. Taconite seals protect the freewheels from contamination with dust or dirt.

Features

Complete Freewheels FRHM with torque arm are sealed sprag freewheels with ball bearings. They are designed for interchanging the Morse® CB units, supplied oil-filled and ready for installation

The freewheels FRHM are arranged on through shafts or shaft ends.

Maximum torques up to 56000 lb-ft.

Bores up to 7 inch.

Application example


Backstop FRHM 900-12 on the head pulley shaft of an inclined conveyor. The back driving torque is restricted by the torque arm on the base plate.


Mounting

The back driving torque is restrained by the torque arm. The torque arm must not be clamped into position. It must have 0.5 inch play in the axial and in the radial direction.

FRHM backstops are supplied for a clearance fit. Set screws on the inner ring are provided for axial retention, shaft collars are not required.

with torque arm with sprags





19-1

Backstop	Standard type For universal use					Dimensions										
Freewheel Size	Maximum torque M _M	Nominal torque M _N lb-ft	Maximum speed inner ring freewheels rpm	Bore d max. inch	A	C	D	E inch	H	J* inch	L* inch	N inch	0 inch	Q	R*	Weight
FRHM 700-7	7500	3750	620	3.44	8.00	4.38	5.25	0.50	21.00	3.56	6.00	1.25	6.63	17.00	15.25	105
FRHM 775-7	15000	7500	540	3.75	9.75	4.38	6.00	0.50	21.88	3.56	7.50	1.25	8.13	17.00	15.25	160
FRHM 800-7	24000	12000	460	4.50	10.50	4.38	7.00	0.50	22.25	3.56	8.00	1.25	8.63	17.00	15.25	190
FRHM 800-12	24000	12000	460	4.50	10.50	4.75	7.00	0.50	25.50	3.56	8.00	1.25	8.63	20.25	18.63	200
FRHM 900-12	37000	18500	400	5.44	12.00	4.75	8.00	0.50	26.25	3.56	7.63	1.25	8.38	20.25	18.63	210
FRHM 900-19	37000	18500	400	5.44	12.00	4.75	8.00	0.88	30.63	3.56	7.63	1.50	8.75	24.63	22.88	220
FRHM 1000-19	56000	28 000	360	7.00	16.50	4.75	9.00	0.88	32.89	3.56	8.75	1.50	9.13	24.63	22.88	270
FRHM 1 000-30	56000	28000	360	7.00	16.50	5.25	9.00	0.88	33.25	3.56	8.75	1.75	9.13	25.00	23.00	275

See page 9 for determination of selection torque.
Keyway dimensions upon request by customers.
* Shaft length L and stirrup position J or pin position R should be considered. These dimensions may vary from the Morse® Series CB.

Complete Freewheels FA

with torque arm with sprags and grease lubrication





Application as

- Backstop
- Indexing Freewheel


For application as backstop in installations with low speeds in freewheeling operation. For application as indexing freewheel in installations with low to medium total number of actuations.

Features

Complete Freewheels FA with torque arm are sprag freewheels with sleeve bearings. They are grease-lubricated and require no maintenance.

Maximum torques up to 3 690 lb-ft.

Bores up to 3.15 inch.




Application example


Two Complete Freewheels FA 57 in the roller feed of a sheet metal processing machine. The indexing freewheel arranged on the left is driven via a bell crank with an adjustable lift. This enables an infinite setting of the feed. The backstop arranged on the right prevents the indexing rollers from running backwards while the indexing freewheel carries out its back stroke. Often, an additional small brake is provided in order to prevent the accelerated sheet metal strip from advancing.

Complete Freewheels FA



with torque arm with sprags and grease lubrication





21-2

ng Freewheel Backstop	Standard type For universal use	Dimensions
Indexin		

			Maximum	Nominal	Max.speed	Bore	C	D	E	Н	L	N	Weight
			torque	torque	inner ring	d							
Free	ewheel		M _M	M _N	freewheels								
	Size	Type				max.							
			lb-ft	lb-ft	rpm	inch	lbs						
FA	37	SF	340	170	250	0.984	1.378	2.992	0.472	3.543	1.378	0.453	2.2
FA	57	SF	930	465	170	1.650	1.969	3.937	0.630	4.921	1.772	0.571	5.5
FA	82	SF	2360	1 180	130	2.560	2.362	5.512	0.709	6.299	2.362	0.827	12.2
FA	107	SF	3690	1845	90	3.350	3.150	6.693	0.787	7.087	2.559	0.886	18.8

See page 9 for determination of selection torque. Keyway dimensions upon request by customers.

Mounting

When used as a backstop, the backdriving torque is supported by the torque arm. The torque arm must not be clamped into position. It must have 0.002 to 0.008 inch play in the axial and radial directions.

When used as an indexing freewheel, the torque arm serves as the indexing lever arm.

The torque arm is not heat treated enabling the customer alter the torque arm to suit his application.

The recommended tolerance of the shaft is +0/-0.001 inch.

Complete Freewheels RFB



with torque arm and clamping collar or mounting flange with sprags and grease lubricated ball bearings



Application as




Features Features

Complete Freewheels RFB are sprag freewheels with sealed grease lubricated ball bearings that require no maintenance. They are supplied with a clamping collar or a flange for direct mounting to standard bushings.

Maximum torques up to 900 lb-ft.

Bores up to 6 inch with clamping collar.




Application example

Complete Freewheel RFB as a backstop on a radial fan. The backstop prevents reverse rotation of the fan shaft from air flow or from incorrectly polarized drive motor.

Complete Freewheels RFB



with torque arm and clamping collar or mounting flange with sprags and grease lubricated ball bearings



See page 9 for determination of selection torque.

Mounting

Backstops RFB are mounted with either a clamping collar to shaft end or a mounting flange that can be connected directly to a QD or Taper Lock bushing.

Additional shaft accessories may be required for RFB-TL designs, contact RINGSPANN.

^{*} A 3/4" inch diameter arm extension is available upon request.

Complete Freewheels FR ... CA


with gear coupling with sprags







Main drive reewheel 1 FRSG 600 CA 2.0 Right angle gear box Freewheel 2 FRZ 500 CA 1.5 Auxiliary drive 24-2



Application as

Overrunning Clutch

Features

Complete Freewheel FR ... CA incorporate a freewheel FR ... and a gear coupling. Freewheels are supplied oil or grease lubricated.

Maximum torques up to 55 000 lb-ft.

Bores up to 7 inch.

Complete Freewheels FR ... CA allow for removal of the assembly without moving the connected equipment. The clutch should always be mounted on the low temperature shaft of the application.


Application Example

Two Complete Freewheels FR ... CA with gear coupling as overrunning clutches in the drive unit of a tube mill with additional auxiliary drive. A freewheel FRSG 600 CA 2.0 (Freewheel 1) is arranged between the main drive and the right angle gear box. A freewheel FRZ 500 CA 1.5 (Freewheel 2) with sprag lift-off Z (page 26) is positioned between the auxiliary drive and the right angle gear box. If the auxiliary drive is operating, Freewheel 2 works in the driving operation and the Freewheel 1 overruns at a low speed (freewheel operation). When driving via the main drive, the unit is driven thru Freewheel 1 (driving operation) Freewheel 2 overruns and automatically disengages the auxiliary drive (freewheeling operation). With the high speed, the type with sprag lift-off Z is used. There is no contact of the sprags during freewheeling and therefore no wear.



25-1

with gear coupling with sprags



Standard type

Standard type

For universal use

Standard type-grease lubricated

For universal use

				Max. s	peed				Max.	speed
	Coup-	Maximum	Nominal	inner ring	outer ring		Maximum	Nominal	inner ring	outer ring
Freewheel	ling	torque	torque	freewheels/	freewheels/	Freewheel	torque	torque	freewheels/	freewheels/
Size	Size	M _M	M _N	overruns	overruns	Size	M _M	M _N	overruns	overruns
		lb-ft	lb-ft	rpm	rpm		lb-ft	lb-ft	rpm	rpm
FRS 300 CA	F 1.0	420	210	2500	2600	FRSG 300 CA	420	210	3600	3600
FRS 400 CA	F 1.0	670	335	1900	2100	FRSG 400 CA	670	335	3600	3600
FRS 500 CA	F 1.5	1 600	800	1400	1 900	FRSG 500 CA	1600	800	3600	3600
FRS 550 CA	F 2.0	3 050	1525	1175	1 600	FRSG 550 CA	3050	1525	3600	3600
FRS 600 CA	F 2.0	3 900	1950	1100	1 500	FRSG 600 CA	3 900	1950	3600	3600
FRS 650 CA	F 2.5	5 400	2700	900	1 250	FRSG 650 CA	5400	2700	3600	3600
FRS 700 CA	F 3.0	11 050	5 5 2 5	790	1150	FRSG 700 CA	11050	5 5 2 5	1800	1800
FRS 750 CA	F 3.5	18700	9350	790	1150	FRSG 750 CA	18700	9350	1800	1800
FRS 775 CA	F 4.0	17 000	8500	750	1 050	FRSG 775 CA	17000	8500	1800	1800
FRS 800 CA	F 4.0	22 200	11 100	700	950	FRSG 800 CA	22 200	11 100	1800	1800
FRS 900 CA	F 4.5	33 600	16800	700	950	FRSG 900 CA	33600	16800	1200	1 200
FRS 1000 CA	F 5.0	55 000	27500	630	800	FRSG 1000 CA	55 000	27500	1200	1200

See page 9 for determination of selection torque.

Freewheel	Bo ma		A	DBSE	E	L1	L2	Weight*
Size	Freewheel d1 inch	Coupling d2 inch	inch	inch	inch	inch	inch	lbs
FR 300 CA	0.750	1.750	4.560	3.500	7.688	2.500	1.688	15
FR 400 CA	1.125	1.750	4.560	3.750	8.188	2.750	1.688	18
FR 500 CA	1.312	2.313	6.000	4.188	9.625	3.500	1.938	32
FR 550 CA	1.625	2.875	7.000	5.000	10.688	3.250	2.438	46
FR 600 CA	2.000	2.875	7.000	4.313	10.500	3.750	2.438	55
FR 650 CA	2.500	3.750	8.375	5.125	11.656	3.500	3.031	91
FR 700 CA	2.938	4.375	9.438	6.875	15.469	5.000	3.594	137
FR 750 CA	3.438	5.000	11.000	8.750	18.938	6.000	4.188	235
FR 775 CA	3.750	5.875	12.500	9.500	20.250	6.000	4.750	321
FR 800 CA	4.500	5.875	12.500	7.688	18.438	6.000	4.750	343
FR 900 CA	5.438	6.500	13.625	9.125	20.813	6.375	5.313	487
FR 1000 CA	7.000 7.125		15.500	10.125	22.781	6.625	6.031	740

^{*} Note Weights are based on Solid Coupling hubs. Weights will vary with required bores. • Keyway dimensions upon request by customers.

Mounting

The gear coupling and stub adapter with fasteners are supplied loose. Depending on the desired freewheeling direction, the gear coupling can me mounted on either the drive or driven shaft.

Labyrinth Seals

Labyrinth seals are available to provide additional protection for harsh environments.


25

Complete Freewheels FRX ... CA and FRZ ... CA



26-1

with gear coupling with sprag lift-off ...



inning Clutch Backstop	Type with sprag lift-off X To extend service life using sprag lift-off for high speed rotating inner ring	Type with sprag lift-off Z To extend service life using sprag lift-off for high speed rotating outer ring
- Verru		
Ó		

					Max. speed						Max. s	peed
	Coup-	Maximum	Nominal	Sprag lift-off	inner ring	outer ring		Max.	Nominal	Sprag lift-off	outer ring	inner ring
Freewheel	ling	torque	torque	at inner ring	freewheels/	drives	Freewheel	torque	torque	at outer ring	freewheels/	drives
Size	Size	M _M	M _N	speed	overruns		Size	M _M	M _N	speed	overruns	
		lb-ft	lb-ft	rpm	rpm	rpm		lb-ft	lb-ft	rpm	rpm	rpm
FRX 400 CA	F 1.0	250	125	860	4000	340	FRZ 400 CA	560	280	800	2600	320
FRX 500 CA	F 1.5	850	425	750	4000	300	FRZ 500 CA	1 070	535	1 400	2050	560
FRX 550 CA	F 2.0	1500	750	700	4000	280	FRZ 550 CA	2760	1380	1550	1800	620
FRX 600 CA	F 2.0	2000	1000	670	4000	265	FRZ 600 CA	3 5 3 0	1765	1450	1650	580
FRX 650 CA	F 2.5	3500	1750	610	3100	240	FRZ 650 CA	5 000	2500	1300	1400	520
FRX 700 CA	F 3.0	8100	4050	350	2600	140	FRZ 700 CA	10 500	5 2 5 0	1160	1200	465
FRX 750 CA	F 3.5	14600	7300	320	2400	125	FRZ 750 CA	17 500	8750	1160	1200	465
FRX 775 CA	F 4.0	14800	7400	320	2100	125	FRZ 775 CA	15 000	6500	950	1050	380
FRX 800 CA	F 4.0	29000	14500	250	1800	100	FRZ 800 CA	17 400	8700	880	975	350
FRX 900 CA	F 4.5	30 000	15 0 0 0	250	650	100	FRZ 900 CA	26 000	13 000	720	925	288

See page 9 for determination of selection torque.


Freewheel	Bo ma		A	DBSE	Е	L1	L2	Weight*
Size	Freewheel d1	Coupling d2	*	1. di	*	t. d.	1.4	U
	inch	inch	inch	inch	inch	inch	inch	lbs
FR 400 CA	1.125	1.750	4.560	3.750	8.188	2.750	1.688	18
FR 500 CA	1.312	2.313	6.000	4.188	9.625	3.500	1.938	32
FR 550 CA	1.625	2.875	7.000	5.000	10.688	3.250	2.438	46
FR 600 CA	2.000	2.875	7.000	4.313	10.500	3.750	2.438	55
FR 650 CA	2.500	3.750	8.375	5.125	11.656	3.500	3.031	91
FR 700 CA	2.938	4.375	9.438	6.875	15.469	5.000	3.594	137
FR 750 CA	3.438	5.000	11.000	8.750	18.938	6.000	4.188	235
FR 775 CA	3.750	5.875	12.500	9.500	20.250	6.000	4.750	321
FR 800 CA	4.500	5.875	12.500	7.688	18.438	6.000	4.750	343
FR 900 CA	5.438	6.500	13.625	9.125	20.813	6.375	5.313	487

^{*} Note Weights are based on Solid Coupling hubs. Weights will vary with required bores. • Keyway dimensions upon request by customers.

Accessories for Complete Freewheels FR...

RINGSPANN®

Torque Arms TA and End Covers



Torque Arm	С	Е	Н	J	N	Q	Weight
	inch	inch	inch	inch	inch	inch	lbs
TA 300	2.00	0.375	8.375	1.000	0.53125	6.250	2
TA 400	2.00	0.375	8.625	1.000	0.53125	6.250	3
TA 500	2.00	0.375	9.000	1.125	0.53125	6.250	3
TA 550	2.25	0.375	10.125	1.375	0.78125	7.000	4
TA 600	2.50	0.375	11.500	1.500	0.78125	8.000	5
TA 650	3.00	0.375	13.625	1.750	0.78125	9.500	6
TA 700	3.00	0.500	15.000	2.000	1.31250	10.500	7
TA 750	3.75	0.500	18.375	2.375	1.28125	12.875	9
TA 775	4.00	0.500	20.000	2.500	1.53125	13.500	14
TA 800	4.00	0.500	21.000	2.750	1.53125	14.625	16
TA 900	4.75	0.875	30.500	3.375	1.53125	22.875	17
TA 1000	5.25	0.875	32.000	3.375	1.78125	23.000	51

Torque Arms TA

Torque Arms TA are offered as an accessory for Freewheels FRS, FRSG and FRX when used as a backstop.

The torque arms are supplied pre-drilled and ready for installation.

Installation

The torque arm must not be rigidly anchored but must be restrained by either a non-threaded pin or an angle iron bracket.

When a pin is used the diameter of the pin must be 1/32 of an inch smaller than the pin hole diameter N of the torque arm.




End Covers


End covers are available to protect operating personnel from coming in contact with the rotating shaft for all Complete Freewheels FR Contact fatory for availability.


Internal Freewheels ZZ ...

with ball bearing properties









Application as

- Backstop
- Overrunning Clutch
- Indexing Freewheel

Features

Internal Freewheels ZZ ... are sprag freewheels with bearing support and ball bearing properties. The freewheels are supplied grease-filled for normal operating conditions.

The freewheel is assembled into the customer housing, allowing a compact, space-saving solution.

Maximum torques up to 480 lb-ft/650 Nm. The torque is transmitted on the inner ring and/or on the outer ring by press fit or keyway connection.

Bores up to 1.575 inch/40 mm.

The following series are available:

Ser	ies		Torque tra			2RS- seals	Page
		oute	rring	inne	ring		
		b	y	b	у		
		keyway	press fit	keyway	press fit		
ZZ			0		•		29
ZZ	2RS		0		0	0	30
ZZ	P2RS		0	•		0	30
ZZ	P		0	0			31
ZZ	PP	0		0			31

The Internal Freewheels ZZ of the sizes ZZ 6201 to ZZ 6207 have the same dimensions as the respective ball bearings of series 62.


The series ZZ ... 2RS and ZZ ... P2RS have 2RS seals.

Application example


Two Internal Freewheels ZZ 6206 as indexing freewheels in the drive of the metering roller of a seed spreader. The freewheels are built in an infinitely variable oil bath gearbox. Two cam disks that are off set by 180° are arranged on the gearbox shaft. By means of torque arms, these drive the outer rings of the two adjacent Internal Freewheels, which then gradually turn the metering shaft. The infinite speed settings of the gearbox's drive shaft are executed by means of the respective pivoting of the roller support plate, so that the torque arms can execute lifts of differing amounts.

RINGSPANN®

for press fit on the outer ring with sprags, bearing supported



29-1



Freewheel	Maxin	num	Nom	inal	Maximum		Load ra			Во	re	Е	3)	K		Weig	ght
Size	torq		tord		speed		bearings	support		C									
	M	Л	М	N		dyna C	mic	sta C											
	lb-ft	Nm	lb-ft	Nm	rpm	lbf	N	lbf	N	inch	mm	inch	mm	inch	mm	inch	mm	lbs	kg
ZZ 8	3.8	5,0	1.9	2.5	15000	720	3 2 0 0	194	860	0.315	8	0.354	9	0.866	22	1.063	27	0.05	0.02
ZZ 6201	13.8	18.6	6.9	9.3	10000	1370	6100	610	2700	0.472	12	0.394	10	1.260	32	1.535	39	0.09	0.04
ZZ 6202	38.6	52.0	19.3	26.0	9400	1350	6000	830	3700	0.591	15	0.433	11	1.378	35	1.654	42	0.14	0.06
ZZ 6203	50.4	68.0	25.2	34.0	8200	1650	7350	1 0 2 5	4550	0.669	17	0.472	12	1.575	40	2.008	51	0.18	0.08
ZZ 6204	96.2	130.0	48.1	65.0	6800	2250	10000	1415	6300	0.787	20	0.551	14	1.850	47	2.283	58	0.26	0.12
ZZ 6205	118.6	160.0	59.3	80.0	5600	2475	11000	1575	7000	0.984	25	0.591	15	2.047	52	2.480	63	0.33	0.15
ZZ 6206	251.8	340.0	125.9	170.0	4000	3 3 7 5	15000	2250	10000	1.181	30	0.630	16	2.441	62	2.874	73	0.55	0.25
ZZ 6207	259.2	350.0	129.6	175.0	3600	2810	12500	1620	7200	1.378	35	0.669	17	2.835	72	3.346	85	0.66	0.30
ZZ 40	481.4	650.0	240.7	325.0	3 0 0 0	3485	15500	2755	12250	1.575	40	0.866	22	3.150	80	3.710	94	1.10	0.50

See page 9 for determination of selection torque.

Mounting

The torque is transmitted on the inner ring and outer ring by press fit. In order to transmit the torques specified in the table, the outer ring must be installed in a housing with an external diameter K. The housing should be made of steel or grey cast iron in minimum quality GG-20. When using other housing materials or smaller external diameters, we urge you to contact us regarding the transmissible torque.

The tolerance of the housing bore D must be ISO N6 and the tolerance of the shaft must be ISO n6

The permissible operating temperature of the freewheel is -40°F to +175°F.

Lubrication


The freewheels are supplied grease-filled for normal operating conditions. However, the freewheels can also be connected to the customer's oil lubrication system; this is particularly recommended in the case of higher speeds.


Internal Freewheels ZZ ... 2RS and ZZ ... P2RS



30-2

for press fit on the outer ring with sprags, bearing supported and sealed





g Freewheel nning Clutch Backstop	Standard type For universal use	Dimensions
Indexing		

30-1

Freev	wheel	Maxir	num	Nom	inal	Maxi-		Load ra	ting of		Во	re	E	3)	K		Weig	ght								
Si	ze	tord	que	torc	que	mum		bearing:	support		d																	
		M	M	М	N	speed	dyna	mic	sta	tic																		
Series	Series														С		C	0										
ZZ 2RS	ZZ P2RS	lb-ft	Nm	lb-ft	Nm	rpm	lbf	N	lbf	N	inch	mm	inch	mm	inch	mm	inch	mm	lbs	kg								
ZZ 8 2RS*		3.8	5.0	1.9	2.5	15000	742	3 300	193	860	0.315	8	0.354	9	0.865	22	1.060	27	0.044	0.02								
ZZ 12 2RS	ZZ 12 P2RS	13.8	18.6	6.9	9.3	10000	1371	6100	630	2800	0.472	12	0.551	14	1.260	32	1.540	39	0.110	0.05								
ZZ 15 2RS	ZZ 15 P2RS	25.2	34.0	12.6	17.0	8400	1663	7400	764	3400	0.591	15	0.630	16	1.378	35	1.654	42	0.154	0.07								
ZZ 17 2RS	ZZ 17 P2RS	44.0	60.0	22.0	30.0	7350	1776	7900	854	3800	0.669	17	0.669	17	1.575	40	2.008	51	0.198	0.09								
ZZ 20 2RS	ZZ 20 P2RS	74.0	100.0	37.0	50.0	6000	2113	9400	1012	4500	0.787	20	0.748	19	1.850	47	2.283	58	0.330	0.15								
ZZ 25 2RS	ZZ 25 P2RS	126.0	170.0	63.0	85.0	5200	2405	10700	1237	5 5 0 0	0.984	25	0.787	20	2.047	52	2.480	63	0.396	0.18								
ZZ 30 2RS	ZZ 30 P2RS	204.4	276.0	102.2	138.0	4200	2630	11700	1461	6500	1.181	30	0.827	21	2.441	62	2.874	73	0.594	0.27								
ZZ 35 2RS	ZZ 35 P2RS	259.2	350.0	129.6	175.0	3600	2832	12600	1641	7300	1.378	35	0.866	22	2.835	72	3.346	85	0.881	0.40								
ZZ 40 2RS	ZZ 40 P2RS	481.4	650.0	240.7	325.0	3 0 0 0	3835	15500	2765	12300 1.575 40 1.063 27 3.150		1.063 27		3.150 80		3.710	94	1.322	0.60									

See page 9 for determination of selection torque.

Mounting

Series ZZ ... 2RS:

The torque is transmitted on the inner ring and outer ring by press fit.

Series ZZ ... P2RS:

The torque is transmitted on the inner ring by keyway connection and on the outer ring by press fit.

In order to transmit the torques specified in the table, the outer ring must be installed in a housing with an external diameter K. The housing should be made of steel or grey cast iron in minimum quality GG-20. When using other housing materials or smaller external diameters, we urge you to contact the factory regarding the transmissible torque.

The tolerance of the housing bore "D" must be ISO N6 and the tolerance of the shaft must be ISO n6.

The permissible operating temperature of the freewheel is $+40^{\circ}$ F to $+140^{\circ}$ F. Please contact the factory if the temperature is different than the given values.

Lubrication

The freewheels are supplied grease-filled and with two RS seals.


Keyway according to DIN 6885, page 3 \bullet Tolerance of keyway width JS10.

^{*} Only one RS seal on the ball bearing side. Locking from this side the freewheeling direction of the inner ring is clockwise free.

Internal Freewheels ZZ ... P and ZZ ... PP



for press fit or keyway connection on the outer ring with sprags, bearing supported



See page 9 for determination of selection torque.

40 P ZZ 40 PP

Keyway according to DIN 6885, page 1 • Tolerance of keyway width JS10.

650.0

240.7

3000

15500

2765

481.4

Mounting

Series ZZ ... P:

The torque is transmitted on the inner ring by keyway connection and on the outer ring by press fit.

Series ZZ ... PP:

The torque is transmitted on the inner and on the outer ring by keyway connection.

In order to transmit the torques specified in the table, the outer ring must be installed in a housing with an external diameter K. The housing should be made of steel or grey cast iron in minimum quality GG-20. When using other housing materials or smaller external diameters, we urge you to contact the factory regarding the transmissible torque.

The tolerance of the housing bore "D" must be ISO N6 and the tolerance of the shaft must be ISO k6.

The permissible operating temperature of the freewheel is $+40^{\circ}$ F to $+140^{\circ}$ F. Please contact the factory if the temperature is different than the given values.

Lubrication

The freewheels are supplied grease-filled.

0.50

^{*} Keyway according to DIN 6885, page 3 • Tolerance of keyway width JS10.

Internal Freewheels RC

RINGSPANN®

for keyway connection on the outer ring with sprags



Application as


- Backstop
- Overrunning Clutch

Features

Internal Freewheels RC are sprag freewheels without inner ring or bearing support. The customer's hardened and ground shaft is used as the inner ring.

Maximum torques up to 1240 lb-ft.

The freewheel is incorporated into the customer's housing, allowing for a compact, space saving solution.



Mounting

Internal Freewheels RC require bearing support and a shaft hardened to HRC 58-62 with a 0.060 inch case depth after grinding to a 16 micro finish. Concentric alignment of the shaft and housing bore is required.

Lubrication

Internal Freewheels RC require either grease or oil lubrication. Lubrications containing molybdenum disulphide must not be used.

Backstop		i rd type ersal use	Dimensions													
Freewheel	Maximum torque M _M	Nominal torque M _N	Housing Bore Diameter D	Freewheel Diameter D	В	Shaft Diameter J	Keyway N x P	Use with bearing	Weight							

F	reewheel Size	torque M _M	torque M _N	Diameter D	D D		Diameter J	NxP		
		lb-ft	lb-ft	inch	inch	inch	inch	inch		lbs
	RC 205	220	110	2.0482	2.0463	1.000	0.929/0.930	3/ ₁₆ x 3/ ₃₂	205	0.75
	RC 206	390	195	2.4422	2.4403	1.125	1.289/1.290	1/4 x 1/8	206	1.00
	RC 207	650	325	2.8360	2.8341	1.125	1.656/1.657	1/ ₄ x 1/ ₈	207	1.25
	RC 208	900	450	3.1510	3.1491	1.250	1.840/1.841	3/8 x 3/16	208	1.75
	RC 210	1240	620	3.5447	3.5248	1.250	2.208/2.209	3/8 x 3/16	210	2.00

See page 9 for determination of selection torque.

Internal Freewheels RCD



specifically designed as an interchange backstop for Dodge® TXT shaft mounted reducers with sprags



Application as

Backstop

Features

Internal Freewheels RCD are sprag freewheels without bearing support. They are specifically designed as interchange backstops for Dodge® shaft mounted reducers.

The freewheel is incorporated into the customer's housing, allowing for a compact, space saving solution.

Interchange Chart

RINGSPANN ^o	TXT Series	Obsolete TXT Series	TDT Series	TD Series	Backstop Part Number
RCD-3	309A 315A 325A				243106
RCD-4	409A 415A 425A				244106
RCD-5	509 515 525 509B 515A 525A 515B 525B				245154
RCD-6	609 615 625 T16	605 No. 16A	615 625 615A 625A	615 625	246092
RCD-7	709 715 725 T17	705 No. 17A	715 725	715 725 715A 725A	247260
RCD-8/9	815 825 915 926 No.8 No.9	No. 18	815 825 915 926 1115 1125	815 825 815A 825A 915 1115 1125	249260
RCD-10/12	1015 1024 1215 1225	805 T 18	1015 1024 1215 1225	926 1015 1024 1215 1225	250260
RCD-13		905	1325		272259

 ${\sf Dodge}^{\circledast} \ {\sf is\ a\ registered\ trademark\ of\ Baldor\ Electric\ Company}.$

Mounting

Internal Freewheels RCD are used to interchange backstops installed by the gearbox manufacturer. Installation instructions and recommendations by the gearbox manufacturer should be followed for the safe operation and longevity of the backstop.

Lubrication

Oil lubrication as specified by the gearbox manufacturer should be used. Lubrications containing molybdenum disulphide must not be used.

Interchange Chart



for Marland, Formsprag, Morse®/EPT and Renold with RINGSPANN Freewheels

RINGSPANN°	Marl	and	Formsprag	Morse®/EPT	Renold
	Clutch	RINGSPANN			
FRS 300	RMS-12N		FSO-/HPI-/HSB-300	MG-/MI-300A	SO/SX300
FRS 400	RMS-14	RMS-14/RMS-18	FSO-/HPI-/HSB-400	MG-/MI-400A	SO/SX400
FRS 500	RMS-21	RMS-21	FSO-/HPI-/HSB-500	MG-/MI-500A	SO/SX500
FRS 550	RMS-26	RMS-26	FSO-/HPI-/HSB 550		
FRS 600	RMS-32	RMS-32	FSO-/HPI-/HSB-600	MG-/MI-600A	SO/SX600
FRS 650	RMS-40	RMS-40	FSO-/HPI-/HSB-650		
FRS 700	RMS-47	RMS-47	FSO-/HPI-/HSB-700	MG-/MI-700A	SO/SX700
FRS 750	RMS-55	RMS-55	HPI-/FS-/HSB-750	MG-/MI-750	SO/SX750
FRS 800	RMS-72	RMS-72	HPI-/FS-/HSB-800	MG-/MI-800	SO/SX800
FRS 900	RMS-87	RMS-87	HPI-/FS-/HSB-900	MG-/MI-900A	SO/SX900
FRS 1 000	RMS-112	RMS-112	HPI-/FS-/HSB-1027	MG-/MI-1 000A	SO/SX1027
FRSG 300	RMS-12 FG			MO-300A*	SO/SX300
FRSG 400	RMS-14 FG	RMS-14 FG/RMS-18 FG		MO-400A*	SO/SX400
FRSG 500	RMS-21 FG	RMS-21 FG		MO-500A*	SO/SX500
FRSG 550	RMS-26 FG	RMS-26 FG			
FRSG 600	RMS-32 FG	RMS-32 FG		MO-600A*	SO/SX600
FRSG 650	RMS-40 FG	RMS-40 FG			
FRSG 700	RMS-47 FG	RMS-47 FG		MO-700A*	SO/SX700
FRSG 750	RMS-55 FG	RMS-55 FG	FSO-750		
FRSG 800	RMS-72 FG	RMS-72 FG	FSO-800		SO/SX800
FRSG 900	RMS-87 FG	RMS-87 FG	FSO-900		SO/SX900
FRSG 1 000	RMS-112 FG	RMS-112 FG	FSO-1027		SO/SX1027
FRX 400	RMI-14	RMX-14	FRB-400		
FRX 500	RMI-21	RMX-21	FRB-500		
FRX 550	RMI-26	RMX-26			
FRX 600	RMI-32	RMX-32	FRB-600		
FRX 650	RMI-40	RMX-40	FRB-650		
FRX 700	RMI-47	RMX-47	FRB-700		
FRX 750	RMI-55	RMX-55	FRB-750		
FRX 800	RMI-72	RMX-72	FRB-800		
FRX 900	RMI-87	RMX-87	FRB-900		
FRHM 775-7				CB 7**	
FRHM 800-7				CB 7**	
FRHM 800-12				CB 12**	
FRHM 900-12				CB 12**	
FRHM 900-19				CB 19**	
FRHM 1 000-19				CB 19**	
FRHM 1 000-30				CB 30**	
RC 205		R205	FS 20-5	B205A	
RC 206		R206	FS 20-6	B206A	
RC 207		R207	FS 20-7	B207A	
RC 208		R208	FS 20-8	B208A	
RC 210	** Interchange is dependent on the	R210	FS 20-10	B210A	

*Grease filled with labyrith seals • ** Interchange is dependent on the maximum required bore of the RINGSPANN FRHM. See Page 19. • Morse is a registered trademark of Borg Warner.

Interchange Chart



FRHD Series - for Formsprag, Marland, Falk, Stephens Adamson and Morse®

Manufacturer	RINGSPANN°	Formsprag	Marland	Falk	Stephens Adamson	Morse [®]				
Size Max. Bore (inch) Torque Rating (lb-ft)	FRHD 700 3.44 33.750	LLH 700 2.94 5000	BC 3MA 2.94 3 000	2.50	HD 215 2.94 3333					
Size Max. Bore (inch) Torque Rating (lb-ft)	FRHD 775 3.75 7 500	LLH 750 3.44 7000	BC 6MA 3.69 6000	3.94	HD 315 3.94 6666	CB 7 2 6500				
Size Max. Bore (inch) Torque Rating (lb-ft)	FRHD 800 4.5 12 000	LLH 800 4.44 13 000	BC 12MA 4.5 12000	3.94	HD 415 4.94 11 667	CB 12 5.25 12 000				
Size Max. Bore (inch) Torque Rating (lb-ft)	FRHD 900 5.44 18500	LLH 900 5.44 18000	BC 18MA 5.44 18 000	5.19	HD 600 6 20 833	CB 19 6.25 19000				
Size Max. Bore (inch) Torque Rating (lb-ft)	FRHD 950 7 23 000	LLH 1027 7 27 000	BC 27MA 6.5 27 000	5.5	HD 700 7 27 083	CB 30 7.75 30 000				
Size Max. Bore (inch) Torque Rating (lb-ft)	FRHD 1 000 7 28 000	LLH 1027 7 27000	BC 27MA 6.5 27 000	5.5	HD 700 7 27 083	CB 30 7.75 30 000				
Size Max. Bore (inch) Torque Rating (lb-ft)	FRHD 1 050 FRHD 1 100 7 7 45 000 45 000	7	BC 45MA 7 45 000	7.44	HD 800 8 45 833	CB 45 8.5 45 000				
Size Max. Bore (inch) Torque Rating (lb-ft)	FRHD 1 200 9 92 500	LLH 1250 9 65 000	BC 63MA 8 63 000	8.44	HD 900 9 66 667	CB 65 9.5 65 000				
Size Max. Bore (inch) Torque Rating (lb-ft)	FRHD 1 300 10 110 000	LLH 1300 10 90 000	BC 90MA 9 90 000	9	HD 1000 10 92500					
Size Max. Bore (inch) Torque Rating (lb-ft)	FRHD 1 400 12 140 000	LLH 1375 11 135 000	BC 135MA 10 135 000	10.5	HD 1200 12 145833	CB 150 11.5 150 000				
Size Max. Bore (inch) Torque Rating (lb-ft)	FRHD 1 450 12 190 000	LLH 2000 13.25 200000	BC 180MA 11.75 180 000	12	HD 1400 14 208333	CB 250 13.5 250 000				
Size Max. Bore (inch) Torque Rating (lb-ft)	FRHD 1 500 12 290 000	LLH 2400 15.5 265 000	BC 240MA BC 300MA 14 14 240 000 300 000	13.25	HD 1600 16 316667					
Size Max. Bore (inch) Torque Rating (lb-ft)	FRHD 1 600 14 373 000	LLH 3500 20 375 000	BC 300MA BC 375MA 14 18 300 000 375 000	15.5	HD 1600 16 316667					
Size Max. Bore (inch) Torque Rating (lb-ft)	FRHD 1 700 18 625 000	LLH 5000 20 700 000	BC 375MA BC 540MA 18 21 375 000 540 000	17.5	HD 1800 18 416666					
Size Max. Bore (inch) Torque Rating (lb-ft)	FRHD 1 800 21 900 000	LLH 5000 20 700 000	BC 720MA BC 940MA 21 21 720 000 940 000	20						
Size Max. Bore (inch) Torque Rating (lb-ft)	FRHD 1 900 21 1 200 000		BC 1 200 MA 23.5 1 200 000							

The above is a functional interchange reference, please verify dimensional interchange details. • Morse® is a registered trademark of Borg Warner

Questionnaire for selecting RINGSPANN Backstops



Please photocopy or use the PDF-File from our website!

Company: Address:		
Address:	Phono	
Name:	Fav.	
Department:	E-mail:	
Where will the Backstop be used?		
1.1 Type of machine: In the case of conveyor belts:	1.3 Arrangement: on a shaft end Diameter: inch	1.4 If possible, please include specification, data sheet, sketch or drawing with con- nection dimensions.
Angle of the steepest segment° Multiple-drive? □ Yes □ No If yes, number of drives	Length: inch on a through shaft Diameter: inch	
1.2 Backstop location: ☐ on the gearbox ☐ on the motor ☐ elsewhere:	on a sprocket elsewhere:	
2.1 Speed at the backstop location (backstop shaft) n _{sp} = rpm Would it be possible to arrange the backstop on a high speed shaft? (higher speed = lower torque = smaller backstop) If neccesary please give further details on the drawing.	 2.2 Nominal power of motor P₀ = hp 2.3 Must the backstop also absorb the peak torque that occurs if the drive motor is started in the locking direction of the backstop (incorrectly poled drive motor)? If yes, the backstop must be substantially oversized. □ Yes □ No 	 2.4 Maximum backdriving torque
3. Installation conditions		
3.1 □ Open, outside □ Open, in a closed room □ In the machine housing □ Lubrication by means of oil bath or oil mist in the machine housing □ Connection to the central lubrication system is possible Name of lubricant: Kinematic viscosity: □ cst □ °F □ °C	 3.2 Should the backstop be releasable? No Yes, in an emergency Yes, frequently 3.3 Ambient temperature on the backstop: from "F to "F 3.4 Other (e.g. accessibility, dust susceptibility and other environmental influences that could be of significance): 	3.5 Are there any elastic elements/components located between the backstop and the installation that is to be backstopped (elastic couplings generate considerable peak torques at the moment of stopping)? ☐ Yes ☐ No
4. Estimated requirements	Dia ang /ang ang b	Diagonhiron
Pieces	Pieces/month	Pieces/year
5. Enclosures ☐ Specifications ☐ Data sheet	☐ Sketch/drawing	

Questionnaire for selecting RINGSPANN Overrunning Clutches



Please photocopy or use the PDF-File from our website!

Company: Address: Name: Department:	Inquiry Ref.: Phone: Fax: E-mail:	
1.1 Type of machine, machine group or installation, in which the overrunning clutch will be used:	ed!	1.2 Arrangement of the overrunning clutch (if possible, please include specification, data sheet, sketch or drawing with connection dimensions).
2. Operating data 2.1 In driving operation the drive of the overrunning clutch will be carried out by: □ Asynchronous motor □ direct start-up □ \(\lambda \to \Delta \text{-start-up} \) □ Other electric motor \(\text{Type:} \) □ Combustion engine \(\text{Type:} \) □ Number of cylinders: \(\) □ Turbine □ Other (please explain in more detail): □ \(\) 2.2 To be transmitted in driving operation: \(\text{Power:} \) □ hp or \(\text{Torque:} \) □ lb-ft	 2.3 Maximum torquelb-ft (Important for drives that develop their maximum torque below their nominal speed.) 2.4 Speed in driving operation:	 2.6 If, upon start up, larger masses are to be accelerated: Moment of inertia: J = lb-ft² Speed of mass: n = rpm 2.7 Torque fluctuations/torsional vibrations during driving operation generate the following torque limits Minimum torque M_{min} = lb-ft Maximum torque M_{max} = lb-ft Min-/Maxtorque is not known 2.8 Daily operating time: hours (hr) thereof (hr) driving operation (hr) freewheeling operation
3. Installation conditions 3.1 Open, outside Open, in a closed room in the machine housing Lubrication by means of oil bath or oil mist in the machine housing Connection to the central lubrication system is possible Name of lubricant: Kinematic viscosity cst	3.2 Ambient temperature on the freewheel: from°F to°F 3.3 Other (e.g. accessibility, dust susceptibility and other environmental influences that could be of significance):	4. Estimated requirements Pieces (one-off) Pieces/month Pieces/year 5. Enclosures Data sheet Sketch/drawing

Questionnaire for selecting RINGSPANN Indexing Freewheels



Please photocopy or use the PDF-File from our website!

Company:		
Address:	Dhana	
Name:	Fax:	
Department:	E-mail:	
1. Where will the Indexing Freewheel be us 1.1 Type of machine, machine group or installation, in which the indexing freewheel will be used:	ed?	1.2 Arrangement of the indexing freewheel (if possible, please include specification, data sheet, sketch or drawing with connection dimensions).
2. Operating data		
 2.1 Index angle of the indexing freewheel: from ° to ° 2.2 Number of actuations (indexes) per minute: from /min to /min 2.3 The back and forth movement is made by	 2.4 The back and forth movement is generated by bell crank hydraulic cylinder pneumatic cylinder cam disk or plate other (please explain in more detail): 	 2.5 Proposed shaft dimensions: Diameter inch Length inch 2.6 Normal torque: M = lb-ft Maximum torque: M_{max} = lb-ft (including peaks) 2.7 Daily operating time: hours
3. Installation conditions 3.1 □ Open, outside □ Open, in a closed room □ in the machine housing □ Lubrication by means of oil bath or oil mist in the machine housing □ Connection to the central lubrication system is possible Name of lubricant: Kinematic viscosity: — cst — °F — °C	3.2 Ambient temperature on freewheel: from °F to °F 3.3 Other (e.g. accessibility, dust susceptibility and other environmental influences that could be of significance):	
4. Estimated requirement Pieces	Pieces/month	Pieces/year
5. Enclosures □ Specifications □ Data sheet	☐ Sketch/drawing	

Notes / sketches



															 	—
															 	_
															 —	 —
															 	 —
															 	 —

RINGSPANN®

Germany

RINGSPANN GmbH

Schaberweg 30-38 61348 Bad Homburg Germany

+49 61 72 275 0 info@ringspann.de www.ringspann.com

RINGSPANN RCS GmbH

Hans-Mess-Straße 7 61440 Oberursel Germany

+49 61 72 67 68 50 info@ringspann-rcs.de www.ringspann-rcs.com

Sweden, Finland, Denmark, Norway, Baltic states

RINGSPANN Nordic AB

Industrigatan 7 61933 Trosa Sweden

+46 156 190 98 info@ringspann.se www.ringspann.se

France

SIAM - RINGSPANN S.A.

23 rue Saint-Simon 69009 Lyon France

+33 4 78 83 59 01 info@siam-ringspann.fr www.ringspann.fr

Netherlands, Belgium, Luxembourg

RINGSPANN Benelux B.V.

Nieuwenkampsmaten 6-15 7472 De Goor Netherlands

+31 547 2613-55 info@ringspann.nl www.ringspann.nl

Switzerland

RINGSPANN AG

Sumpfstrasse 7 6300 Zug Switzerland

+41 41 748 09 00 info@ringspann.ch www.ringspann.ch

Great Britain, Ireland

RINGSPANN (U.K.) LTD.

3, Napier Road Bedford MK41 0QS Great Britain

+44 12 34 34 25 11 info@ringspann.co.uk www.ringspann.co.uk

Austria, Hungary, Slovenia

Edmayr Antriebstechnik GmbH Thalham 20 4880 St. Georgen Austria +43 7667 684 0

+43 7667 684 0 office@edmayr.at www.ringspann.com

Spain, Portugal

RINGSPANN IBERICA S.A.

C/Uzbina, 24-Nave E1 01015 Vitoria Spain

+34 945 22 77-50 info@ringspann.es www.ringspann.es

Italy

Osvaldo Alioli Via Borghetto, 41 20033 Desio Italy

+39 33 88 13 15 14 alioliringspann@alioli.191.it www.ringspann.com

Poland

RADIUS-RADPOL sp.j. Wiecheć, Labacki ul. Kolejowa 16b 60 185 Skórzewo Poland

+48 61 814 39 28 info@radius-radpol.com.pl www.radiusradpol.pl

Czech Republic, Slovakia

Ing. Petr Schejbal Mezivrší 1444/27 147 00 Praha Czech Republic +420 222 96 90 22 Petr.Schejbal@ringspann.cz www.ringspann.com

Asia

Australia, New Zealand

Kempower Pty. Ltd. 6 Phoenix Court, Braeside 3195 Victoria Australia

+61 3 95 87 90 33 dirk@imtec-kempower.com.au www.imtec-kempower.com.au

China, Taiwan

RINGSPANN Power Transmission (Tianjin) Co., Ltd.

No. 21 Gaoyan Rd. Binhai Science and Technology Park Binhai Hi-Tech Industrial Development Area Tianjin, 300458 P.R. China

+86 22 59 80 31 60 info.cn@ringspann.cn www.ringspann.cn

India, Bangladesh, Nepal

RINGSPANN Power Transmission India Pvt. Ltd.

GAT No: 679/2/1 Village Kuruli, Taluka Khed Chakan-Alandi Road Pune - 410501 India

+91 2135 677 500 info@ringspann-india.com www.ringspann-india.com

Singapore, ASEAN

RINGSPANN Office Arthur Low 1 Scotts Road #21-10 Shaw Centre Singapore 228208 +65 9633 6692

Arthur.Low@ringspann.com www.ringspann.com

America

USA, Canada, Mexico, Chile, Peru

RINGSPANN Corporation

10550 Anderson Place Franklin Park, IL 60131 U.S.A

+1 847 678-3581 info@ringspanncorp.com www.ringspanncorp.com

Africa and Middle East

Egypt

Shofree Trading Co. 218 – emtedad Ramsis (2) 2775 Nasr City Cairo Egypt

+20 2 24 01 88 89 info@shofree.com www.ringspann.com

noam a@gg.co.il

www.ringspann.com

Algeria, Morocco, Tunisia

SIAM - RINGSPANN S.A.

23 rue Saint-Simon 69009 Lyon France

+33 4 78 83 59 01 info@siam-ringspann.fr www.ringspann.fr

Iran

Rastan Felez Taha Eng Trading Co (RFT) Unit No. 8 461, North Kargar Avenue

Iran +98 21 88 00 94 35 info@rftrft.com www.ringspann.com

Tehran postal code 1413683164

Israel

G.G. Yarom Rolling and Conveying Ltd. 6, Hamaktesh Str. 58810 Holon Israel +972 3 557 01 15

South Africa, Sub-Saharan

RINGSPANN Transmission Components (Pty) Ltd.

96 Plane Road Spartan Kempton Park P.O. Box 8111 Edenglen 1613 South Africa

+27 11 394 18 30 info@ringspann.co.za www.ringspann.co.za